



Features:

- ### Rear Panel:



Specification:

Model		BA-120Z	BA-240Z	BA-350Z	BA-500Z
Description	3 Zone Mixer Amplifier with ATT/Mp3/USB/FM/Bluetooth				
Rated Power Output	60W	120W	240W	350W	500W
Speaker Output	3 zone speaker outputs of 100V One zone speaker outputs of 40hm-80hm-160hm-70V-100V				
Input	Mic1-3: 2.5mV, Mic1(6.3mm) and Mic/Line input 2-3 (COMBO XLR) Aux1-2: 250mV, RCA 24V mute control input to trigger the built-in chime/Alert/EVAC pre-recorded messages				
Frequency Response	80-16KHz				
THD	<0.1%				
S/N Ratio	>70dB				
Protection	High temp, short circuit, clip & overload protection				
Power Supply	230V AC, 50-60Hz				
Power Consumption	100W	200W	400W	500W	650W
Dimension	484×405×88mm				
Weight	7.5	7.7kg	8.7kg	10.2g	10.3kg

Connection Diagram:

